

SDAQ update SOP

1. Open DAQPilot ACE, select the device that needs to be updated, and click **claim**.

Unclaimed devices			
Model ↑↓	Device ↑↓	IP	Claim Device ↑↓
 SDAQ-204	2371100FK0	172.30.80.72	claim
 EMU-200	EMU200	192.168.50.2	claim

2. After entering the username and password to complete the claim, you can start the update.
Username: administrator; Password: Adlink6166


Claim SDAQ-204-0-003064735eb3 (2371100FK0) ×

Username

Password

× Cancel ✓ Claim

3. Click **Update** to start updating the device.

Model ↑↓	Device ↑↓	IP
 SDAQ-204	SDAQ-204-0-003064735eb3	172.30.80.72

1

...

2

- Dashboard
- IP Setting
- Remove iApp
- Update**
- unclaim

4. If this SDAQ is being updated for the first time, you will need to wait for some preprocessing time.
※ Please note that with this update method, the SDAQ firmware version must not be lower than 23.12.1222.

Update

Firmware Version: 23.12.1222



Setting things up, please wait for a while...

5. Select the dedicated file (**SDAQ200_vxx.xx.xxxx.bin**) for updating the SDAQ, and click **Update** to start the update process.
※ The update process takes about 20 minutes. Do not turn off the SDAQ during this time, as it will cause the update to fail.

Update

Firmware Version: 23.12.1222

+ SDAQ200_v24.10.0913.bin

↑ Upgrade

Upgrading ...

5/7

Step 5/7: Installing ./sdaq-iapp-agent_24.09.0913_armhf.deb ...

⚠ Warning: To avoid any damage, keep the device powered on.

- Once the completion message appears, you can close the window and verify whether the version has been successfully updated.

Update




Firmware Version: 23.12.1222

+ SDAQ200_v24.10.0913.bin

Upgrade

Done. You can close this window.

- To complete the process, click back to the Update page to confirm whether the version has been successfully updated.

Model ↑↓	Device ↑↓
 SDAQ-204	SDAQ-204-0-003064735eb3 ...

- Dashboard
- IP Setting
- Remove iApp
- Update
- unclaim

Update

Firmware Version: 24.10.0913

+ Choose

Upgrade